

# advanced devices

## Catalog # CL20FR

### CL Series Female Receptacle

---

Panel Mount 300A/600V, Double Set Screw  
NEMA 3R, 4 when mated with shrouded device.

---

- Use #2 to 2/0 cable, copper.
- Strip wire jacket 1-3/4 inch.
- Wrap foil around strands, insert into contact and tighten setscrews (2) to 150 in.-lbs. of torque. Do not over tighten.

**CAUTION:** The female cam alignment button on cam –type devices will withstand up to approximately 40 ft.-lbs. of torque. Care should be exercised when attaching a "Hard 3-fer" to a panel mount. Excessive torque applied to the 3-fer may result in a collapse of the cam button.



# advanced devices

## Catalog # CL20FR

### CL Series Female Receptacle

---

Panel Mount 300A/600V, Double Set Screw  
NEMA 3R, 4 when mated with shrouded device.

---

- Use #2 to 2/0 cable, copper.
- Strip wire jacket 1-3/4 inch.
- Wrap foil around strands, insert into contact and tighten setscrews (2) to 150 in.-lbs. of torque. Do not over tighten.

**CAUTION:** The female cam alignment button on cam –type devices will withstand up to approximately 40 ft.-lbs. of torque. Care should be exercised when attaching a "Hard 3-fer" to a panel mount. Excessive torque applied to the 3-fer may result in a collapse of the cam button.



# advanced devices

## Catalog # CL20FR

### CL Series Female Receptacle

---

Panel Mount 300A/600V, Double Set Screw  
NEMA 3R, 4 when mated with shrouded device.

---

- Use #2 to 2/0 cable, copper.
- Strip wire jacket 1-3/4 inch.
- Wrap foil around strands, insert into contact and tighten setscrews (2) to 150 in.-lbs. of torque. Do not over tighten.

**CAUTION:** The female cam alignment button on cam –type devices will withstand up to approximately 40 ft.-lbs. of torque. Care should be exercised when attaching a "Hard 3-fer" to a panel mount. Excessive torque applied to the 3-fer may result in a collapse of the cam button.



# advanced devices

## Catalog # CL20FR

### CL Series Female Receptacle

---

Panel Mount 300A/600V, Double Set Screw  
NEMA 3R, 4 when mated with shrouded device.

---

- Use #2 to 2/0 cable, copper.
- Strip wire jacket 1-3/4 inch.
- Wrap foil around strands, insert into contact and tighten setscrews (2) to 150 in.-lbs. of torque. Do not over tighten.

**CAUTION:** The female cam alignment button on cam –type devices will withstand up to approximately 40 ft.-lbs. of torque. Care should be exercised when attaching a "Hard 3-fer" to a panel mount. Excessive torque applied to the 3-fer may result in a collapse of the cam button.

